



OXFORD ELECTRICAL PRODUCTS

audio transformers low profile

0800 316 6060

[get an online quote](#)


[get a catalogue delivered](#)

[download entire catalogue](#)

[can't find what you're looking for ??..](#)


[back to catalogue index](#)

[home](#)



This range of transformers is encapsulated with a flame retardant resin into a very low profile potting box measuring approximately 32x27x15mm high. An optional Mu-Metal screening can be available if required.

On all versions pin 3 is the inter-winding screen. Pin 7 or 9, (see schematics), is connected to the laminations and the flux strap.



Z3001E LOW IMPEDANCE MATCHING TRANSFORMER

1:1 600:600


20 Hz - 20 kHz \pm 0.2 dB

THD < 1% @ +20 dB

Common Mode Rejection Ratio < -60dB @ 10 kHz

Fitted with an electrostatic screen (Scr. 1)

Stray flux screen (Scr. 2)



Z3002E HIGH IMPEDANCE MATCHING TRANSFORMER


1:1 10K:10K

20 Hz - 20 kHz \pm 0.2 dB

THD < 1% @ +20 dB

Common Mode Rejection Ratio < -60dB @ 10 kHz

Fitted with an electrostatic screen and stray flux screen



Z3003E HIGH IMPEDANCE MATCHING TRANSFORMER

1+1:2 2.5K/10K:10K

20 Hz - 20 kHz \pm 0.2 dB

C.M.R.R. < -60dB @ 10 kHz

THD < 1% @ +20 dB

Fitted with an electrostatic screen and stray flux screens