

Square With 5Φ Dome 4 Lead Super Yellow LED Technical Data Sheet

Part No.: LL-U48UY3C-Y2-3B

Spec No.: BNH116 X085 Rev No.: V.3 Date: Jan./25/2006 Page: 1 OF 7

Approved: 34000 Checked: Wu Drawn: Shu



Features:

- ♦ Fewer LEDs required.
- ♦ Low profile.
- ♦ Lowers lighting system cost.
- ♦ Super flux output.
- ♦ Viewing angle=80°.
- ♦ The product itself will remain within RoHS compliant Version.

Descriptions:

- ♦ This revolutionary package design allows the light designer to reduce the number of LEDs required and provide a more uniform and unique illuminated appearance than with other LED solutions.
- ♦ The low profile package can be easily coupled with reflectors or lenses to efficiently distribute light and provide the desired light appearance.

Applications:


- ♦ Automotive exterior lighting.
- ♦ Electronic signs and signals.
- ♦ Special lighting application.


Spec No.: BNH116 X085 Rev No.: V.3 Date: Jan./25/2006 Page: 2 OF 7


Approved: 34000 Checked: Wu Drawn: Shu




Package Dimension:









Part No.	Chip Material	Lens Color	Source Color	
LL-U48UY3C-Y2-3B	AlGaInP	Water Clear	Super Yellow	

Notes:

- 1. All dimensions are in millimeters (inches).
- 2. Tolerance is \pm 0.25mm (.010") unless otherwise noted.
- 3. An epoxy meniscus may extend about 1.50mm (.059") down the leads.
- 4. Specifications are subject to change without notice.

Spec No.: BNH116 X085 Rev No.: V.3 Date: Jan./25/2006 Page: 3 OF 7

Approved: 34000 Checked: Wu Drawn: Shu



Absolute Maximum Ratings at Ta=25℃

Parameters	Symbol	Max.	Unit
Power Dissipation	PD	182	mW
Peak Forward Current (1/10 Duty Cycle, 0.1ms Pulse Width)	IFP	100	mA
Forward Current	IF	70	mA
Reverse Voltage	VR	5	V
Electrostatic Discharge (HBM)	ESD	2000	V
Operating Temperature Range	Topr	-40℃ to +85℃	
Storage Temperature Range	Tstg	-40℃ to +100℃	
Lead Soldering Temperature	Tsld	260℃ for 5 Seconds	

Electrical Optical Characteristics at Ta=25℃

Parameters	Symbol	Min.	Тур.	Max.	Unit	Test Condition
Luminous Intensity *	IV	270	450		mcd	IF=20mA (Note 1)
Viewing Angle *	2θ _{1/2}		80		Deg	IF=20mA (Note 2)
Peak Emission Wavelength	λр		592		nm	IF=20mA
Dominant Wavelength	λd		590		nm	IF=20mA (Note 3)
Spectrum Radiation Bandwidth	Δλ		15		nm	IF=20mA
Forward Voltage	VF	1.60	2.20	2.60	V	IF=20mA
Reverse Current	IR			10	μΑ	V _R =5V

Notes:


- 1. Luminous Intensity (Flux) is measured with a light sensor and filter combination that approximates the CIE eye-response curve.
- 2. $\theta_{1/2}$ is the off-axis angle at which the luminous intensity is half the axial luminous intensity.
- 3. The dominant wavelength (λd) is derived from the CIE chromaticity diagram and represents the single wavelength which defines the color of the device.


Spec No.: BNH116 X085 Rev No.: V.3 Date: Jan./25/2006 Page: 4 OF 7


Approved: 34000 Checked: Wu Drawn: Shu





Typical Electrical / Optical Characteristics Curves (25°C Ambient Temperature Unless Otherwise Noted)






















Spec No.: BNH116 X085 Rev No.: V.3 Approved: 3400 Checked: Wu

Lucky Light Electronics Co., Ltd.

Date: Jan./25/2006 Page: 5 OF 7

Drawn: Shu

http://www.luckylight.cn



Reliability Test Items And Conditions:

The reliability of products shall be satisfied with items listed below:

Confidence level: 90%.

LTPD: 10%.

1) Test Items and Results:

Test Item	Standard Test Method	Test Conditions	Note	Number of Damaged
Resistance to Soldering Heat	JEITA ED-4701 300 302	Tsld=260±5℃, 10sec 3mm from the base of the epoxy bulb	1 time	0/100
Solder ability	JEITA ED-4701 300 303	Tsld=235±5℃, 5sec (using flux)	1time over 95%	0/100
Thermal Shock	JEITA ED-4701 300 307	0℃~100℃ 15sec, 15sec	100 cycles	0/100
Temperature Cycle	JEITA ED-4701 100 105	-40℃~25℃~100℃~25℃ 30min,5min,30min,5min	100 cycles	0/100
Moisture Resistance Cycle	JEITA ED-4701 200 203	25℃~65℃~-10℃ 90%RH 24hrs/1cycle	10 cycles	0/100
High Temperature Storage	JEITA ED-4701 200 201	Ta=100℃	1000hrs	0/100
Terminal Strength (Pull test)	JEITA ED-4701 400 401	Load 10N (1kgf) 10±1sec	No noticeable damage	0/100
Terminal Strength (bending test)	JEITA ED-4701 400 401	Load 5N (0.5kgf) 0°~90°~0° bend 2 times	No noticeable damage	0/100
Temperature Humidity Storage	JEITA ED-4701 100 103	Ta=60℃, RH=90%	1000hrs	0/100
Low Temperature Storage	JEITA ED-4701 200 202	Ta=-40℃	1000hrs	0/100
Steady State Operating Life		Ta=25℃, IF=30mA	1000hrs	0/100
Steady State Operating Life of High Humidity Heat		Ta=60℃, RH=90%, IF=30mA	500hrs	0/100
Steady State Operating Life of Low Temperature		Ta=-30℃, IF=20mA	1000hrs	0/100

2) Criteria for Judging the Damage:

Thom	Symbol Test Conditions	Tost Conditions	Criteria for Judgment		
Item		Min	Max		
Forward Voltage	VF	IF=20mA		F.V.*)×1.1	
Reverse Current	IR	VR=5V		F.V.*)×2.0	
Luminous Intensity	IV	IF=20mA	F.V.*)×0.7		

*) F.V.: First Value.

Spec No.: BNH116 X085 Rev No.: V.3 Date: Jan./25/2006 Page: 6 OF 7

Approved: 34000 Checked: Wu Drawn: Shu



Please read the following notes before using the product:

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

2. Storage

- 2.1 Do not open moisture proof bag before the products are ready to use.
- 2.2 Before opening the package, the LEDs should be kept at 30℃ or less and 90%RH or less.
- 2.3 The LEDs should be used within a year.
- 2.4 After opening the package, the LEDs should be kept at 30℃ or less and 70%RH or less.
- 2.5 The LEDs should be used within 168 hours (7 days) after opening the package.

3. Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than 260°C for 5 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

4. Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.

5. Caution in ESD

Static Electricity and surge damages the LED. It is recommended to use a wrist band or anti-electrostatic glove when handling the LED. All devices equipment and machinery must be properly grounded.

Spec No.: BNH116 X085 Rev No.: V.3 Date: Jan./25/2006 Page: 7 OF 7

Approved: 34000 Checked: Wu Drawn: Shu