

Quectel RM502Q-AE

IoT/eMBB-Optimized 5G Sub-6 GHz M.2 Module



Quectel RM502Q-AE is a 5G module optimized specially for IoT/eMBB applications. Adopting the 3GPP Rel-15 LTE technology, it supports both 5G NSA and SA modes. Designed in an M.2 form factor, RM502Q-AE is compatible with Quectel LTE-A Cat 6 module EM06, Cat 12 modules EM12-G/EM120R-GL/EM121R-GL and Cat 16 module EM160R-GL, which facilitates customers' migration from LTE-A to 5G.

RM502Q-AE is an industrial-grade module for industrial and commercial applications only.

The Global version RM502Q-AE nearly covers all the mainstream carriers worldwide. The module supports Qualcomm® IZat™ location technology Gen9C Lite (GPS, GLONASS, BeiDou/Compass and Galileo). The integrated GNSS receiver greatly simplifies the product design and provides quicker, more accurate and more dependable positioning capability.

A rich set of Internet protocols, industry-standard interfaces and abundant functionalities (USB and PCIe drivers for Windows 7/8/8.1/10, Linux, Android) extend the applicability of the module to a wide range of eMBB and IoT applications such as industrial router, home gateway, STB, industrial laptop, consumer laptop, industrial PDA, rugged tablet PC, video surveillance and digital signage.



Key Features

- ✓ 5G/4G/3G multi-mode module with M.2 form factor, optimized for IoT and eMBB applications
- ✓ Worldwide 5G and LTE-A coverage
- ✓ Both NSA and SA modes supported
- ✓ Multi-constellation GNSS receiver available for applications requiring fast and accurate fixes in any environment
- ✓ Feature refinements: DFOTA and VoLTE (optional)



5G NR Sub-6 Bands Supported



DL: LTE Cat 20
UL: LTE Cat 18



DL: max. 42 Mbps
UL: max. 5.76 Mbps



Embedded Abundant Protocols



M.2 Form Factor



Multi-constellation GNSS



USB 3.1/PCIe 3.0 High Speed Interface



Voice over LTE (Optional)



Quectel Enhanced AT Commands

Quectel RM502Q-AE

| 5G Sub-6 | | RM502Q-AE |
|-------------------------------|---|---|
| Region/Operator | Global (Except for China) | |
| Dimensions (mm) | 30.0 × 52.0 × 2.3 | |
| Weight (g) | 8.7 | |
| Temperature Range | | |
| Operation Temperature | -30 °C to +70 °C | |
| Extended Temperature | -40 °C to +85 °C | |
| Frequency Bands | | |
| 5G | 5G NR | 3GPP Release 15 NSA/SA operation, Sub-6 GHz |
| | 5G NR NSA | n1/n2/n3/n5/n7/n8/n12/n20/n25/n28/n38/n40/n41/n48*/n66/n71/n77/n78/n79 |
| | 5G NR SA | n1/n2/n3/n5/n7/n8/n12/n20/n25/n28/n38/n40/n41/n48*/n66/n71/n77/n78/n79 |
| | MIMO | DL: 4 × 4 MIMO on n1/n2/n3/n7/n25/n38/n40/n41/n48*/n66/n77/n78/n79 UL: 2 × 2 MIMO on n41 |
| LTE Category | | |
| LTE | LTE-FDD | B1/B2/B3/B4/B5/B7/B8/B12(B17)/B13/B14/B18/B19/B20/B25/B26/B28/B29/B30/B32/B66/B71 |
| | LTE-TDD | B34/B38/B39/B40/B41/B42/B43/B48 |
| | LAA | B46 (only support 2 × 2 MIMO) |
| | MIMO | DL: 4 × 4 MIMO on B1/B2/B3/B4/B7/B25/B30/B32/B34/B38/B39/B40/B41/B42/B43/B48/B66 |
| UMTS | WCDMA | B1/B2/B3/B4/B5/B6/B8/B19 |
| GNSS | GPS/GLONASS/BeiDou (Compass)/Galileo | |
| Certifications | | |
| Regulatory | GCF (Global) | |
| | CE (Europe) | |
| | PTCRB (North America) | |
| | FCC (America) | |
| | IC (Canada) | |
| | JATE*/TELEC* (Japan) | |
| Carrier | Verizon*/AT&T*/T-Mobile* (America) | |
| | Telstra* (Australia) | |
| Others | RoHS/WHQL | |
| Data Rate (Max.) ^① | | |
| 5G SA Sub-6 | DL 4.2 Gbps; UL 450 Mbps | |
| 5G NSA Sub-6 | DL 5.0 Gbps; UL 650 Mbps | |
| LTE | DL 2.0 Gbps; UL 200 Mbps | |
| WCDMA | DL 42 Mbps; UL 5.76 Mbps | |
| Interfaces | | |
| (U)SIM | x 1 | |
| USB 2.0 | x 1 | |
| USB 3.0/3.1 | x 1 | |
| PCIe 3.0 | x 1 | |
| PCM | x 1 | |
| Antenna | x 4 | |
| Voice | | |
| VoLTE | Digital Audio and VoLTE (Voice over LTE) (Optional) | |

Notes:

- ①: The presented data rates are theoretical only, and the actual value depends on network conditions.
- *: Under development/in progress.

Quectel RM502Q-AE

| 5G Sub-6 | RM502Q-AE |
|----------------------------|---|
| Enhanced Features | |
| eSIM* (Optional) | ● |
| DTMF* | ● |
| DFOTA* | ● |
| (U)SIM Card Detection | ● |
| Drivers | |
| USB Serial Driver | Windows 7/8/8.1/10; Linux 2.6–5.4; Android 4.x/5.x/6.x/7.x/8.x/9.x/10 |
| GNSS Driver | Android 4.x/5.x/6.x/7.x/8.x/9.x/10 |
| RIL Driver | Android 4.x/5.x/6.x/7.x/8.x/9.x/10 |
| NDIS Driver | Windows 7/8/8.1/10 |
| MBIM Driver | Windows 10; Linux 3.18–5.4 |
| GobiNet Driver | Linux 2.6–5.4 |
| QMI_WWAN Driver | Linux 3.4–5.4 |
| Electrical Features | |
| Supply Voltage Range | 3.135–4.4 V, typical 3.7 V |
| Power Consumption | 80 μ A @ Power down |
| | 4.2 mA @ Sleep |
| | 39 mA @ USB 2.0, Idle |
| | 54.5 mA @ USB 3.0, Idle |

Notes:

- 1.*: Under development/in progress.
- 2.●: supported.