




APPLICATIONS

- SPEAKER
- BUZZER
- HEADPHONE
- MAGNETIC BUZZER
- TELEPHONE MIC
- GENERAL
- TELEPHONE RECEIVER

SELECTION GUIDE FOR DYNAMIC TYPE

Application	Model	SIZE		Sensitivity (dB)	Impedance (ohms)	W (g)
		Diameter (mm)	Height (mm)			
TELEPHONE MIC	DM-96	35.0	18.0	-63.0	150	33.0
 GENERAL	DM-74G	27.0	17.7	-71.5	400	22.0
	DM-74GT2	29.0	20.1	-72.0	400	24.0
	DM-82	19.7	11.8	-83.0	200	10.0
	DM-67	24.0	16.0	-76.0	400	15.0
	DM-60	25.0	18.5	-72.5	500	26.0
	DM-80	20.0	16.0	-78.0	400	15.0
	DM-83A	28.0	25.8	-76.0	500	29.0
	DM-85G	24.5	31.5	-74.0	600	43.0
	DM-99	19.8	14.7	-66.0	200	-
	DM-103	20.8	21.6	-77.0	500	12.0
	DM-107	27.0	21.1	-74.0	500	12.0
	DM-108	27.0	30.7	-74.5	600	33.0

Application	Model	SIZE		Operating Frequency (Hz)	DCR-ohm (Ω)	Rated Voltage (V)	W (g)
		Diameter (mm)	Height (mm)				
	MB-11A	11x13	2.5	2670	7 Ω	DC0.8~1.7V	0.90
	MB-11B	11x13	2.5	2670	28 Ω	DC3.0~4.0V	0.90

MAGNETIC BUZZER	MB-13A	11x13	3.0	2670	7Ω	DC0.8~1.7V	1.00
	MB-13B	11x13	3.0	2670	28Ω	DC3.0~4.0V	1.00
	MB-13C	11x13	3.0	2670	40Ω	DC4.5~5.5V	1.00
	MB-14A	9	4.0	2670	7Ω	DC1.1~1.7V	0.60
	MB-14B	9	4.0	2670	28Ω	DC3.0~4.0V	0.60
	MB-14TA	9 pin	5.0	2670	7Ω	DC1.1~1.7V	0.80
	MB-14TB	9 pin	5.0	2670	28Ω	DC3.0~4.0V	0.80
	MB-15A	9	5.5	2670	7Ω	DC0.8~1.7V	0.60
	MB-15DS	9	5.5	2400	20Ω	DC2.0~3.6V	0.60
	MB-18A	8.5x8.5	2.8	2670	7Ω	DC0.8~1.7V	0.47
	MB-18B	8.5x8.5	2.8	2670	24Ω	DC1.4~4.5V	0.49
	MB-18D	8.5x8.5	2.8	2670	20Ω	DC1.0~3.3V	0.49
	MB-19AM	8.5x8.5	4.0	2475	7Ω	DC0.6~1.7V	0.56
	MB-19D	8.5x8.5	4.0	2670	20Ω	DC1.1~3.3V	0.56
	MB-19DM	8.5x8.5	4.0	2475	20Ω	DC1.1~3.3V	0.56
	MB-14DM3	9	4.0	2670	20Ω	DC2.0~4.5V	0.60
	MB-14DM2	9	4.0	2670	16Ω	DC2.0~3.3V	0.60
	MB-15DM	9	5.5	2670	20Ω	DC2.0~4.5V	0.60
	MB-15DM2	9	5.5	2670	16Ω	DC2.0~3.3V	0.60
	MB-16DM3	13x11	2.5	2670	20Ω	DC2.0~4.5V	0.70
	MB-17DM2	13x11	3.0	2670	16Ω	DC2.0~3.6V	0.80
MB-17DM3	13x11	3.0	2670	20Ω	DC2.0~4.5V	0.80	



Copyright (C) 1998 Primo (Singapore)
 Last updated: November 2002